

# Sound Devices 302 or 442 Mixer



The **Sound Devices 442** is a professional 4 input, portable audio mixer designed for mixing audio in film, ENG / EFP, video and broadcast applications. The mixer features 4 balanced 3-pin XLR inputs capable of accepting microphone and line signal (user switchable on every input). The output stage features stereo (L/R) XLR outputs with individually switchable mic, line or -10dB output impedance. Every input features a dedicated "Direct Output", which is used to distribute audio to external devices. +48V, +12V and +12V-T phantom power is available and is individually switchable on every channel. Each channel features peak limiter and low-cut filter dials as well as volume, gain and pan controls. Channels 1 & 2 can be linked for stereo monitoring or M-S stereo decoding. The unit is powered with 4 - AA alkaline batteries or external 5-18V DC.

The **Sound Devices 302** is a professional, compact 3 channel audio mixer designed to meet the demands of professional film, ENG / EFP and broadcast applications. Its compact design, extensive feature set and superior audio quality justify the mixer's popularity among industry professionals. The 302 features 3 balanced XLR inputs that are capable of accepting mic or line-level signal (user switchable). The output stage features stereo (L/R) balanced XLR outputs that are also mic or line level switchable (factory set to line, refer to manual for mic level set up).

302 Manual: [302 Manual \(PDF Download\)](#)

302 Quick Set Up: [302 Quick Set-Up \(PDF Download\)](#)

442 Manual: [442 Manual \(PDF Download\)](#)